



Antron Electronics Co.,LTD
安雄電子股份有限公司

T8 Program Start Ballast



Model Name	PPQ-A32T8MHO
Ballast Type	Electronic
Starting Method	Program Start
Lamp connection	Parallel
Input Voltage	120-277V
Input Frequency	50/60Hz
Warranty	5 Years $TC \leq 75^{\circ}C$ 3 Years $75^{\circ}C \leq TC \leq 90^{\circ}C$


Safety & Performance



Energy
Verified

- Three or Four Lamps
- UL/cUL Listed
- UL Type 1 Outdoor
- FCC part 18 Class A
- Sound Rated Class A
- Class P Thermally Protected
- High Power Factor
- Surge Protected
- Auto Restart
- No PCBs
- Type HL
- DOE Energy Verified


Wire Diagram



Lead Length	Inch	Cm
Black	18.8	48
White	18.8	48
Blue	30.9	78.5
Red	30.9	78.5
Yellow	46.4	118
Blue/White	30.9	78.5
Brown	30.9	78.5

Maximum Wiring Distance (at full load) is 18AWG/18Feet
Case must be grounded

Enclosure



AM105

Enclosure	Inch	Cm
Length(L)	9.5	24.1
Width(W)	2.4	6.1
Height(H)	1.45	3.7
Mounting(M)	8.9	22.6



Electrical Specification with Different Lamps

Lamp Type	No. of Lamps	Input Voltage (V)	Rated Lamp Watts	Start Temp Min. (F/C)	Input Current (Amps)	Input Power (ANSI Watts)	Ballast Factor	THD Max. (%)	Power Factor	Lamp Current Crest Factor Max.	BEF
F32T8	4	120	32	0/-18	1.17	141	1.2	10	0.99	1.7	0.85
		230			0.58			10	0.99		
		277			0.49			10	0.99		
	3	120	32	0/-18	0.93	109	1.28	10	0.99	1.7	1.17
		230			0.49			10	0.99		
		277			0.4			10	0.99		
F25T8	4	120	25	0/-18	0.86	101	1.24	10	0.99	1.7	1.23
		230			0.45			10	0.99		
		277			0.38			15	0.99		
	3	120	25	0/-18	0.74	87	1.34	15	0.98	1.7	1.54
		230			0.39			15	0.98		
		277			0.33			15	0.97		
F17T8	4	120	17	0/-18	0.65	77	1.26	15	0.98	1.7	1.64
		230			0.35			15	0.98		
		277			0.30			15	0.97		
	3	120	17	0/-18	0.61	72	1.37	15	0.98	1.7	1.90
		230			0.32			15	0.98		
		277			0.27			20	0.97		
F40T8	4	120	40	32/0	0.93	110	1.05	10	0.99	1.7	0.95
		230			0.49			10	0.99		
		277			0.4			10	0.99		



Electrical Specification with Different Lamps

Lamp Type	No. of Lamps	Input Voltage (V)	Rated Lamp Watts	Start Temp Min. (F/C)	Input Current (Amps)	Input Power (ANSI Watts)	Ballast Factor	THD Max. (%)	Power Factor	Lamp Current Crest Factor Max.	BEF
F32T8/ES (30W)	4	120	30	32/0	1.15	137	1.2	10	0.99	1.7	0.88
		230			0.55			10	0.99		
		277			0.47			10	0.99		
	3	120	30	32/0	0.88	105	1.28	10	0.99	1.7	1.22
		230			0.47			10	0.99		
		277			0.40			10	0.99		
F32T8/ES (28W)	4	120	28	32/0	0.88	106	1.2	10	0.99	1.7	1.13
		230			0.48			10	0.99		
		277			0.41			10	0.99		
	3	120	28	32/0	0.74	89	1.28	10	0.99	1.7	1.44
		230			0.39			10	0.98		
		277			0.33			15	0.98		
F32T8/ES (25W)	4	120	25	32/0	0.73	88	1.2	10	0.99	1.7	1.36
		230			0.39			10	0.98		
		277			0.33			15	0.98		
	3	120	25	32/0	0.64	77	1.28	10	0.99	1.7	1.66
		230			0.33			10	0.98		
		277			0.27			15	0.97		